



# MacBook Air 13" Retina Display 2019 Display Replacement

Use this guide to replace the display on a 2019...

Written By: Adam O'Camb



# INTRODUCTION

Use this guide to replace the display on a 2019 MacBook Air.

---

## TOOLS:

[P5 Pentalobe Screwdriver Retina MacBook Pro and Air](#) (1)  
[Tweezers](#) (1)  
[Spudger](#) (1)  
[T3 Torx Screwdriver](#) (1)  
[T5 Torx Screwdriver](#) (1)  
[TR9 Torx Security Screwdriver](#) (1)

## PARTS:

[MacBook Air 13" \(Late 2018-Early 2020\) Display Assembly](#) (1)  
[Display Assembly Compatible with MacBook Air 13" \(Late 2018-Early 2020\)](#) (1)

---

## Step 1 — Remove the screws securing the lower case



- i** Before starting this procedure, you should disable your Mac's **Auto Boot** feature. Auto Boot powers on your Mac when you open the lid, and may be accidentally triggered during disassembly. [Use this guide](#) to disable Auto Boot.
- If your MacBook is running Big Sur v11.1 or later, disabling Auto Boot may not work. You can proceed normally, but make sure to disconnect the battery as soon as you're inside.

**⚠** Completely power off and unplug your MacBook Air before you start. Close the display and flip the entire laptop upside-down.


- Use a P5 driver to remove the following screws:
  - Two 7.9 mm screws
  - Two 7.1 mm screws
  - Six 2.6 mm screws

## Step 2 — Remove the lower case




- Wedge your fingers between the display and the lower case and pull upward to pop the lower case off the Air.
- Remove the lower case.
- ★ After reassembly, your MacBook might not turn on until it's connected to a power source (a low power phone charger may work). To test your repair, plug in your charger, allow two minutes for your MacBook to turn on, and check that everything works as expected.

## Step 3 — Disconnect the battery




- Peel back the tape covering the battery connector enough to reveal the connector underneath.

## Step 4



- Use a spudger to slide the battery connector parallel to the logic board and out of its socket on the logic board.


## Step 5 — Disconnect the antenna bar



- Use a T3 Torx driver to remove the two 1.4 mm screws securing the antenna cable bracket.
- Remove the antenna cable bracket.




## Step 6



- Insert the point of a spudger under one of the antenna cables close to the connector.
- Pry straight up to disconnect the cable.
- Repeat for the other antenna cable.

## Step 7




- Use a T3 Torx driver to remove the two 1.5 mm screws securing the display cable connector bracket.
- Remove the display cable connector bracket.

## Step 8



- Use the flat end of a spudger to pry up the display cable connector.

## Step 9




- Use a T5 Torx driver to remove the following screws:
  - Four 7.4 mm screws
  - Two 4.5 mm screws

## Step 10 — Remove the antenna bar



- Lift the antenna bar straight up and out of the case. Take care not to snag the antenna bar on any cables or connectors.
  - ⓘ You may encounter resistance from the clips in the middle of the antenna bar holding it in the case. You may pull hard without damaging anything as long as you pull straight up, perpendicular to the case.
- Remove the antenna bar.

## Step 11 — Remove the display



- Use a T9 Torx driver to remove the six 4.9 mm screws securing the display hinges to the upper case.



## Step 12



- With the MacBook still screen-side down, carefully lift the upper case to open the MacBook as far as possible.

## Step 13



- Lift the MacBook and carefully rotate the display to a 90 degree angle with the upper case.
  - ① The hinges should not move in relation to the display, and should rotate out of the case slightly.
- Keeping the display at a 90 degree angle with the case, move the display straight down while holding the case still, so that the hinges slide out the bottom of the case.

---

Compare your new replacement part to the original part—you may need to transfer remaining components or remove adhesive backings from the new part before installing.

**To reassemble your device, follow the above steps in reverse order.**

Take your e-waste to an [R2 or e-Stewards certified recycler](#).

Repair didn't go as planned? Check out our [Answers community](#) for troubleshooting help.